

OBLICZENIA SPADKÓW NAPIĘĆ **Obwód nr 2**

STARSZY INŻYNIER

Moment obciążenia-faza L1

| lp | L | P | Moment |
|----|-------|------------|---------------|
| | m | W | Wm |
| 1 | 25 | 70 | 1750 |
| 2 | 133 | 70 | 11060 |
| 3 | 132 | 70 | 20300 |
| 4 | 133 | 70 | 29610 |
| 5 | 119 | 70 | 37940 |
| 6 | 139 | 70 | 47670 |
| 7 | 133 | 70 | 56980 |
| 8 | | 70 | 56980 |
| 9 | | | 0 |
| 10 | | | 0 |
| | Razem | 560 | 260540 |

Moment obciążenia-faza L2

| lp | L | P | Moment |
|----|-------|------------|---------------|
| | W | W | Wm |
| 1 | 69 | 70 | 4830 |
| 2 | 133 | 70 | 14140 |
| 3 | 132 | 70 | 23380 |
| 4 | 134 | 70 | 32760 |
| 5 | 119 | 70 | 41090 |
| 6 | 138 | 70 | 50750 |
| 7 | | | 0 |
| 8 | | | 0 |
| 9 | | | 0 |
| 10 | | | 0 |
| | Razem | 420 | 166950 |

OBLICZENIA SPADKÓW NAPIĘĆ Obwód nr 2

Moment obciążenia-faza L3

| Lp | L | P | Moment |
|----|-------|-----|--------|
| | m | W | Wm |
| 1 | 113 | 70 | 7910 |
| 2 | 133 | 70 | 17220 |
| 3 | 133 | 70 | 26530 |
| 4 | 134 | 70 | 35910 |
| 5 | 124 | 70 | 44590 |
| 6 | 133 | 70 | 53900 |
| 7 | | | 0 |
| 8 | | | 0 |
| 9 | | | 0 |
| 10 | | | 0 |
| | Razem | 420 | 186060 |

| Suma momentów [Wm] | |
|--------------------|--------|
| faza L1 | 260540 |
| faza L2 | 166950 |
| faza L3 | 186060 |
| Razem | 613550 |

| Suma mocy [W] | | |
|---------------|-----|-----|
| L1 | L2 | L3 |
| 560 | 420 | 420 |
| 1400 | | |

| Spadek napięcia | |
|--------------------------------|--|
| (uśredniony) | |
| dla kabla AL35 mm ² | |
| % | |
| 0,35 | |